



Philips Circular
Circular energy saving bulb

25 W

Normal cap Cool daylight

871150031705610

Truly efficient

Lots of light for shallow lamp shades

Circular lamps have a special shape for special applications. Low in height they fit in shallow places, yet they give the extra boost of light - at 80% energy saving.

Special fit

- Slim shape for shallow places

PHILIPS
sense and simplicity

Circular energy saving bulb
25 W Normal cap Cool daylight

871150031705610

Specifications

Technical specifications

- Starting time: 0,2 s
- Power factor: 0,9
- Mercury content: 4 mg
- Lifetime of lamp: 6 year(s)
- Rated lifetime: 6 year(s)
- Rated power: 25 W
- Wattage: 25 W
- Lamp dimension (height): 77,5 mm
- Color rendering index (CRI): 80
- Wattage equivalent: 120 W
- Lamp current: 190 mA
- Lamp dimension (width): 227,2 mm
- Lumen: 1740
- Rated luminous flux: 1740 lm
- Number of switch cycles: 5000
- Lifetime of lamp: 6000 hour(s)
- Rated lifetime: 6000 hour(s)

- Color temperature: 6500 K
- Lumen maintenance factor: 0.7 (at the end of the nominal lifetime) %
- Voltage: 220-240 V
- Warm up time 60% light output: 5 - 30 s
- Energy efficiency label: A
- Shape: Circular
- Color: Cool Daylight
- Fitting/Cap: E27
- Dimmable: No
- Light effect / finish: White
- Wattage standard bulb: 120 W

Cleaning by breakage/disposal

- Cleaning: Follow the advice for proper clean up*
- Disposal: Follow the instruction for disposal as special waste**

Highlights

Slim shape

Special luminaires require special lamps. This product is designed to fit shallow luminaires, where there is limited space available.



Issue date 2011-04-27

Version: 1.0.1

12 NC: 9296 898 19609
EAN: 87 11500 31705 6

© 2011 Koninklijke Philips Electronics N.V.
All Rights reserved.

Specifications are subject to change without notice.
Trademarks are the property of Koninklijke Philips Electronics N.V. or their respective owners.

www.philips.com

* Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and offer it to the local waste facilities for recycling. Do not use a vacuum cleaner.

** Compact fluorescent lamps have to be treated as special waste, they must be offered to the local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass, etc.